

INSTALLATION INSTRUCTIONS SHEET

START FROM HERE

- Make sure power is completely off at the fuse box.
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in clear area.
- Wear gloves at all times during this installation.
- Read instructions carefully before you start assembly.
- Keep this instruction sheet for future reference.



Technical Support: 1-844-628-8368

Please Note:


- All Matteo Lighting fixtures come with pre-wired module(s).
- Unless instructed to do so, please do not touch any part of the module(s) as any unnecessary contact with the module could cause permanent damage.

THIS LUMINAIRE MUST BE MOUNTED OR SUPPORTED INDEPENDENTLY
OF AN OUTLET BOX

CE LUMINAIRE NE DOIT PAS ETRE MONTE SUR UNE BOITE DE SORTIE
NI SUPPORTE PAR UNE TELLE BOITE



NUMERICAL SEQUENCE



- 1 Ensure main supply is switched off.
- 2 Fit mounting bracket (1) onto mounting surface with self-tapping screws (2).
- 3 Put the glass shade (3) onto the ceiling base (4).
- 4 Connect wires (5) according to colour (White to White, Black to Black). Connect all ground wire together onto the crossbar with green, screw to tight.
- 5 Fit ceiling plate onto mounting bracket with nuts (6).
- 6 Hang crystals (A, B, C, D ,E, F, G, H, I) onto ceiling plate according to the numerical sequence.
- 7 Install the bulbs (7) (not included) firmly into lampholders.
- 8 Reconnect power.